

CLAIMS

What is claimed is:

1. A PN code hopping method for mitigating cross-correlation interference, the method comprising the steps of:

providing a memory device;

storing a plurality of orthogonal PN codes in the memory device;

pseudo-randomly accessing the memory device to retrieve one of the plurality of PN codes, wherein each of the plurality of PN codes is associated with a useful life cycle before another PN code is pseudo-randomly retrieved; and

spreading a modulated data signal with the retrieved one of the plurality of PN codes.

2. A method as in claim 1 wherein the step of storing the plurality of orthogonal PN codes in the memory device further comprises the steps of:

storing unbalanced orthogonal PN codes in the memory device; and

storing balanced orthogonal PN codes in the memory device.

3. A method as in claim 2 wherein the step of storing unbalanced orthogonal PN codes in the memory device further comprises the step of storing Gold PN codes.

4. A method as in claim 1 wherein the step of pseudo-randomly accessing the memory device to retrieve one of the plurality of PN codes further comprises the steps of:

providing an addressable multiplexer;

coupling the addressable multiplexer to the memory device;

clocking a PN-code from the memory device to the addressable multiplexer;

pseudo-randomly selecting an input address of the addressable multiplexer; and

outputting from the multiplexer a PN-code associated with the selected input address.

5. A method as in claim 4 wherein the step of clocking the PN-code from the memory device further comprises the step of clocking the PN-code at a rate equal to a symbol rate.

6. A method as in claim 4 wherein the step of clocking the PN-code from the memory device further comprises the step of clocking the PN-code at a rate equal to a integer multiple of a symbol rate.

7. A method as in claim 4 wherein the step of pseudo-randomly selecting an input address of the addressable multiplexer further comprises the step of constraining the pseudo-random selection to select the input address based upon a previously selected one of the plurality of PN codes.

8. A method as in claim 4 wherein the step of pseudo-randomly selecting an input address of the addressable

multiplexer further comprises the step of constraining the pseudo-random selection to select the input address based upon a previously selected input address.

9. A method as in claim 1 wherein the useful lifecycle comprises N symbol periods, where $N = 1, 2, 3, \dots$.

10. A method as in claim 1 wherein the step of spreading the modulated data signal with the retrieved one of the plurality of PN codes further comprises the steps of:

spreading a phase shift keying (PSK) modulated signal with the retrieved one of the plurality of PN codes for the useful life cycle associated with the retrieved one of the plurality of PN codes.

11. A pseudo-noise (PN) code hopping device, the device comprising:

at least one memory device, wherein the at least one memory device comprises:

a plurality of time limited PN codes;

an addressable multiplexer, wherein the addressable multiplexer is coupled to the at least one memory device; and

an address generator, wherein the address generator is coupled to the addressable multiplexer.

12. A PN code hopping device as in claim 11 wherein the at least one memory device further comprises:

a N-x-Spreading Factor (SF) storage capacity, where
 N = number of chips and $SF = N/\text{symbol}$; and

N-parallel outputs.

13. A PN code hopping device as in claim 11 wherein the
 at least one memory device further comprises:

a N-x-Spreading Factor (SF) storage capacity, where
 N = number of chips and $SF = N/\text{symbol}$;

a universal serial bus (USB) port; and

a serial to N-parallel converter.

14. A PN code hopping device as in claim 11 wherein the
 addressable multiplexer comprises a $N:1$ multiplexer where
 N = number of chips associated with one of the plurality
 of time limited PN codes.

15. A PN code hopping device as in claim 11 wherein the
 address generator comprises a look-up-table (LUT).

16. A PN code hopping device as in claim 11 wherein the
 address generator comprises a shift register.

17. A PN code hopping device as in claim 11 wherein the
 address generator comprises:

an up-down counter; and

a look-up-table, wherein the look-up-table is
 coupled to the up-down counter.

18. A PN code hopping system for mitigating cross-correlation interference between Direct Sequence-Code Division Multiple Access (DS-CDMA) users, the system comprising:

a first PN code hopping module, wherein the first PN code hopping module comprises:

a first memory device;

a first addressable multiplexer, wherein the addressable multiplexer is coupled to the first memory device;

a first address generator, wherein the first address generator is coupled to the first addressable multiplexer;

a second PN code hopping module, the second PN code hopping module is coupled to the first PN code hopping module, wherein the second PN code hopping module comprises:

a second memory device;

a second addressable multiplexer, wherein the addressable multiplexer is coupled to the second memory device; and

a second address generator, wherein the second address generator is coupled to the second addressable multiplexer.

19. A PN code hopping system as in claim 18 wherein the first memory device comprises:

a first modulation matrix of size $L \times L$, where $L = SF_{\max}/SF_{\min}$, wherein the first modulation matrix comprises a first set of time limited PN codes; and

M^0-M^{L-1} parallel outputs.

20. A PN code hopping system as in Claim 18 wherein the first addressable multiplexer comprises a M^0-M^{L-1} multiplexer.

21. A PN code hopping system as in Claim 18 wherein the first address generator comprises:

a first up-down counter; and

a first look-up-table (LUT), the first LUT coupled to the first up-down counter.

22. A PN code hopping system as in Claim 18 wherein the first address generator comprises a first shift register.

23. A PN code hopping system as in claim 18 wherein the second memory device comprises:

a second modulation matrix of size $P \times nP$, where $P = SF_{\max}/L$, $L = SF_{\max}/SF_{\min}$, $n = \text{PN order}$, and wherein the second modulation matrix comprises a second set of time limited PN codes; and

G^0-G^{P-1} parallel outputs.

24. A PN code hopping system as in Claim 18 wherein the second addressable multiplexer comprises a G^0-G^{P-1} multiplexer.

25. A PN code hopping system as in Claim 18 wherein the second address generator comprises:

a second up-down counter; and

a second look-up-table (LUT), the second LUT coupled to the second up-down counter.

26. A PN code hopping system as in Claim 18 wherein the second address generator comprises a second shift register.

27. A program storage device readable by a machine, tangibly embodying a program of instructions executable by the machine to perform method steps for mitigating cross-correlation interference, the method comprising the steps of:

storing a plurality of orthogonal PN codes in the memory device;

pseudo-randomly accessing the memory device to retrieve one of the plurality of PN codes, wherein each of the plurality of PN codes is associated with a useful life cycle before another PN code is pseudo-randomly retrieved; and

spreading a modulated data signal with the retrieved one of the plurality of PN codes.

28. A PN code hopping method for mitigating cross-correlation interference between adjacent cells, the method comprising the steps of:

providing a first set of PN spreading codes, the first set of PN spreading codes comprising:

a first subset of hoppable PN codes;

a second subset of non-hoppable PN codes, wherein the second subset of non-hoppable PN codes is used for system control purposes, the second subset of non-hoppable PN codes comprising:

at least one PN spreading code;

providing a memory device;

storing the first set of PN codes in the memory device;

pseudo-randomly accessing the memory device to retrieve one of the first subset of hoppable PN codes;

spreading a modulated data signal with the retrieved one of the first subset of hoppable PN codes.

29. A method as in claim 28 wherein the step of spreading the modulated data signal further comprises the step of spreading the modulated data for a time substantially equal to an integer multiple of a symbol time.